

WHAT IS CLAIMED IS:

1. A band-division demodulation method in which a transmission band of a received RF signal is band-divided into a plurality, each of signals said band-divided is OFDM-demodulated, and said demodulation results are synthesized,

wherein the received RF signal is in-phase-distributed to said band division number, the band width that the entire band width of said received RF signal is divided by said band division number is used as a unit band width, each signal said distributed so as to be shifted stepwise by integral times of said unit band width is frequency-converted, each signal said frequency-converted is allowed to band-pass by filtering with the same characteristics to perform a band division, and said signal allowed to band-pass is OFDM-demodulated.

2. An OFDM receiver in which a transmission band of a received RF signal is band-divided into a plurality, each of signals said band-divided is OFDM-demodulated, and said demodulation results are synthesized, comprising:

a distribution section for receiving an RF signal and in-phase-distributing it to said band division number;

a frequency conversion section for using, as a unit band width, the band width that the entire band width of said received RF signal is divided by said band division number, and frequency-converting each signal said distributed so as

to be shifted stepwise by integral times of said unit band width;

a band-pass filter section for allowing each signal said frequency-converted to band-pass with the same characteristics;

an OFDM demodulation section for OFDM-demodulating said signal allowed to band-pass; and

a synthesizing section for synthesizing an output from said OFDM demodulation section to output demodulated data.

3. The OFDM receiver according to claim 2, wherein said band-pass filter section is a band-pass filter section of the same characteristics for allowing a frequency band that each signal said frequency-converted has in common.

4. An OFDM receiver in which a transmission band of a received RF signal is band-divided into a plurality, each of signals said band-divided is OFDM-demodulated, and said demodulation results are synthesized, comprising:

a first frequency conversion section for receiving an RF signal and converting it into a first IF frequency band;

an AGC section for adjusting an output signal from said first frequency conversion section to a certain constant output level and outputting it;

an in-phase distributor for in-phase-distributing an

output from said AGC section into said band width division number;

5 a second frequency conversion section for using, as a unit band width, the band width that the entire band width of said received RF signal is divided by said band division number, and frequency-converting each output from said in-phase distributor so as to be shifted stepwise by integral times of said unit band width;

10 a band-pass filter section for allowing each signal said frequency-converted to band-pass with the same characteristics;

a third frequency conversion section for frequency-converting said each band-pass signal into a second IF frequency band;

15 an OFDM demodulation section for OFDM-demodulating an output from said third frequency conversion section; and

a P/S section for parallel-to-series-converting and synthesizing an output from said each OFDM demodulation section.

20 5. An OFDM receiver in which a transmission band of a received RF signal is band-divided into a plurality, each of signals said band-divided is OFDM-demodulated, and said demodulation results are synthesized, comprising:

25 an AGC section for receiving an RF signal, adjusting it to a certain constant output level, and outputting it;

an in-phase distributor for in-phase-distributing an

output from said AGC section into said band width division number;

5 a fourth frequency conversion section for frequency-converting each output from said in-phase distributor, using, as a unit band width, the band width that the entire band width of said received RF signal is divided by said band division number, and frequency-converting each output from said in-phase distributor so as to be shifted stepwise by integral times of said unit band width;

10 a band-pass filter section for allowing each signal said frequency-converted to band-pass with the same characteristics;

15 a fifth frequency conversion section for frequency-converting said each band-pass signal into a second IF frequency band;

an OFDM demodulation section for OFDM-demodulating an output from said fifth frequency conversion section; and

20 a P/S section for parallel-to-series-converting and synthesizing an output from said each OFDM demodulation section.

6. An OFDM receiver in which a transmission band of a received RF signal is band-divided into a plurality, each of signals said band-divided is OFDM-demodulated, and said demodulation results are synthesized, comprising:

an AGC section for receiving an RF signal, adjusting it to a certain constant output level, and outputting it;

an in-phase distributor for in-phase-distributing an output from said AGC section into said band width division number;

5 a fourth frequency conversion section for frequency-converting each output from said in-phase distributor, using, as a unit band width, the band width that the entire band width of said received RF signal is divided by said band division number, and frequency-converting each output from said in-phase distributor so as to be shifted stepwise by integral times of said unit band width;

10 a band-pass filter section for allowing each signal said frequency-converted to band-pass with the same characteristics;

5 an OFDM demodulation section for inputting an output from said band-pass filter section, under-sampling it by a frequency lower than a usual sampling frequency in accordance with the frequency of said input signal to convert it into a digital signal, and OFDM-demodulating it; and

20 a P/S section for parallel-to-series-converting and synthesizing an output from said each OFDM demodulation section.

7. A multi-carrier transmission system having a transmitter for OFDM-modulating and transmitting a transmission signal, and a receiver for receiving and OFDM-demodulating said radio transmission signal,

wherein said receiver is the OFDM receiver according

to claim 2.

8. A multi-carrier transmission system having a transmitter for OFDM-modulating and transmitting a transmission signal, and a receiver for receiving and OFDM-demodulating said radio transmission signal,

wherein said receiver is the OFDM receiver according to claim 3.

9. A multi-carrier transmission system having a transmitter for OFDM-modulating and transmitting a transmission signal, and a receiver for receiving and OFDM-demodulating said radio transmission signal,

wherein said receiver is the OFDM receiver according to claim 4.

10. A multi-carrier transmission system having a transmitter for OFDM-modulating and transmitting a transmission signal, and a receiver for receiving and OFDM-demodulating said radio transmission signal,

wherein said receiver is the OFDM receiver according to claim 5.

11. A multi-carrier transmission system having a transmitter for OFDM-modulating and transmitting a transmission signal, and a receiver for receiving and OFDM-demodulating said radio transmission signal,

wherein said receiver is the OFDM receiver according to claim 6.

12. A multi-carrier transmission system having a transmitter for OFDM-modulating and transmitting a transmission signal, and a receiver for receiving and OFDM-demodulating said radio transmission signal,

wherein said receiver is the OFDM receiver according to claim 7.

Parameter	Value
10	0.000000
11	0.000000
12	0.000000
13	0.000000
14	0.000000
15	0.000000
16	0.000000
17	0.000000
18	0.000000
19	0.000000
20	0.000000
21	0.000000
22	0.000000
23	0.000000
24	0.000000
25	0.000000
26	0.000000
27	0.000000
28	0.000000
29	0.000000
30	0.000000
31	0.000000
32	0.000000
33	0.000000
34	0.000000
35	0.000000
36	0.000000
37	0.000000
38	0.000000
39	0.000000
40	0.000000
41	0.000000
42	0.000000
43	0.000000
44	0.000000
45	0.000000
46	0.000000
47	0.000000
48	0.000000
49	0.000000
50	0.000000
51	0.000000
52	0.000000
53	0.000000
54	0.000000
55	0.000000
56	0.000000
57	0.000000
58	0.000000
59	0.000000
60	0.000000
61	0.000000
62	0.000000
63	0.000000
64	0.000000
65	0.000000
66	0.000000
67	0.000000
68	0.000000
69	0.000000
70	0.000000
71	0.000000
72	0.000000
73	0.000000
74	0.000000
75	0.000000
76	0.000000
77	0.000000
78	0.000000
79	0.000000
80	0.000000
81	0.000000
82	0.000000
83	0.000000
84	0.000000
85	0.000000
86	0.000000
87	0.000000
88	0.000000
89	0.000000
90	0.000000
91	0.000000
92	0.000000
93	0.000000
94	0.000000
95	0.000000
96	0.000000
97	0.000000
98	0.000000
99	0.000000